

SAFETY INSTRUCTIONS

IMPORTANT

This unit should be installed to current IET wiring regulations, if in doubt consult a qualified electrician.

1. Disconnect the mains supply before proceeding with the installation.
2. These products should be connected to a lighting circuit or fused at a maximum of 5A.
3. The transformer incorporated in these products has an isolating 20VA loading and an output of 230V or 115V on the dual voltage version and 230V on the single.
4. Ensure products plugged into this unit are rated less than 20VA.

INSTALLATION INSTRUCTIONS

These units must be mounted horizontally on a vertical surface. Please read the instructions fully before attempting



Fig.1

installation and retain for future reference.

1. Remove the diffuser by gently pressing the sides at the point indicated, in Fig.1, and lift out.
2. Remove the back plate of the shaver light and using as a template mark fixings in the required position on the wall, and drill fixing holes accordingly.
3. Connect the cable by passing through the hole in the back plate and follow the codes as listed:
Live (L) = Brown or Red, Neutral (N) = Blue or Black, conductor size 0.5mm to 1.5mm solid or stranded, ensure that no strands of cable are visible outside the connector.
4. Place shaver light into position with back plate secured, and screw onto wall with appropriate screws through the holes in the base of the unit.
5. Insert the lamp and replace diffuser.
6. Switch back on the mains supply and shaver light is now ready for use.

Safety Note:

The unit will not work if the diffuser is not in place.

LAMP REPLACEMENT

Remove the tube by gently pushing it sideways into the right hand or left hand socket and lift out from the socket. See Fig. 2




Fig. 2

Note:

Before plugging in the shaver, select the correct out put voltage (230 or 115) with the switch provided (dual voltage version only).

TECHNICAL INFORMATION

Power Rating:	230V 50Hz supply 115V/230V output
IP Rating:	IP20
Max Rating:	60W
Transformer:	20VA overload protected
Insulation:	Double insulated transformer
Diffuser:	Safety interlocked
Dimensions:	H60 X W495 x D70mm
Lamp Type:	284mm S15 double cap
Compatible with:	LED or incandescent lamps

NOTE:

Product & Packaging Disposal

When disposing of this item and its packaging please follow local regulations and use an appropriate waste disposal centre.

PLEASE KEEP THESE INSTRUCTIONS
SAFE FOR FUTURE REFERENCE

UK
CA

CE

